



Amplification Chart



V1.0 Release Date: 2025.6.6

Amplifier Speaker Pairings

										
	Product	Amp Channels Used	# Per Circuit	# Per Amp	# Per Circuit	# Per Amp	# Per Circuit	# Per Amp	# Per Circuit	# Per Amp
Large Format	E15	4	N/A	N/A	1	1	2	2	1	2
	E12	4	N/A	N/A	1	1	3	3	1	2
	E219	2	N/A	N/A	1	1	2	2	1	2
	E119	1	N/A	N/A	1	3	2	5	1	5
	IS219	1	N/A	N/A	N/A	N/A	1	2	N/A	N/A
Sub Compact	S10 / S10n / IS10 / IS10n	2	1	2	2	4	4	8	2	8
	S10p / IS10p	2	1	2	2	4	4	8	2	8
	S119 / IS119	1	N/A	N/A	1	4	2	6	1	6
	IS213	1	N/A	N/A	N/A	N/A	2	5	N/A	N/A
Ultra Compact	S7	2	1	2	2	4	4	8	2	8
	IS7	2	N/A	N/A	3	12	6	12	3	12
	S7p Bi-Amped / IS7p	2	1	2	2	4	4	8	2	8
	S7p Passive / IS7px	1	1	3	2	8	4	13	2	13
	IS7c	1	3	6	4	16	8	26	4	26
	IS5c	1	4	16	6	24	12	48	6	48
	S118 / IS118	1	1	4	2	8	4	16	2	16
Monitor Series	M10 Bi-Amped	2	1	2	2	4	4	8	2	8
	M10 Passive	1	1	2	2	7	3	12	2	12
	M15A	2	1	2	2	4	4	8	2	8
	M15P	1	1	4	1	4	3	12	1	8
	M12A	2	1	2	2	4	4	8	2	8
	M12P	1	1	4	1	4	3	12	1	8
	M212	2	2	4	2	4	2	3	N/A	N/A
Point Series	P8P	1	2	6	3	12	4	16	3	24
	P115P + P8P	1	N/A	N/A	N/A	N/A	1	4	N/A	N/A
	P115A	1	1	4	2	8	3	12	2	16
	P215	1	N/A	N/A	1	4	2	8	1	8
	PC5	1	1	4	2	8	2	8	2	16
	PC8	1	1	4	2	8	2	8	2	16

» Release Notes

V1.0

First release of this document.